
**Item code 86.SD07.1303.02**




• Installation and wiring of luminaire must be in accordance with all applicable local codes.
• Installation, inspection, and maintenance of luminaires should be performed by a qualified electrician.
• DO NOT make or alter any open holes in the luminaire. Do not modify the luminaire.
• DO NOT install damaged product.
• Make sure electrical power is OFF before and during installation and maintenance.
• Make sure the equipment is properly grounded.
• Make sure the supply voltage is same as the rated fixture voltage.

**LED Ceiling light**
**DOR/DOS**





**IP54**

**Required Tools**



**WARNING:**





Check that the power is off before conducting any maintenance and assembly work




Caution,danger of electric shock



The installation and commissioning of the luminaire as well as any modification to the luminaire may only be performed by authorized personnel (qualified electrician).


Step:1
STEP:2
DOR420: 190mm
DOR260/DOR320: 120mm
DOS260/DOS320: 120mm
DOR420: 190mm
OPTION:A
OPTION:B
>35mm
STEP:3
STEP:4
AUTO CLICK
OPTION--SAFETY COVER
CLICK
PUSH


## I. WIRING DIAGRAMS: CCT+POWER/SWITCHABLE




| Switching selection sheet | | | |
|---|---|---|---|
| Out Power Range | Irated | 1 | 2 |
| 6-8.5W | 115mA | - | - |
| 8-10W | 140mA | ON | - |
| 12-14.5W | 200mA | ON | ON |

| Switching selection sheet | | | |
|---|---|---|---|
| Out Power Range | Irated | 1 | 2 |
| 8-10W | 140mA | - | - |
| 12-14.5W | 200mA | ON | - |
| 16-20.5W | 280mA | ON | ON |


## II. WIRING DIAGRAMS: CCT+POWER/SWITCHABLE+SENSOR/EM2




| Switching selection sheet | | | |
|---|---|---|---|
| Out Power Range | Irated | 1 | 2 |
| 6-8.5W | 115mA | - | - |
| 8-10W | 140mA | ON | - |
| 12-14.5W | 200mA | ON | ON |

| Switching selection sheet | | | |
|---|---|---|---|
| Out Power Range | Irated | 1 | 2 |
| 8-10W | 140mA | - | - |
| 12-14.5W | 200mA | ON | - |
| 16-20.5W | 280mA | ON | ON |

## III. WIRING DIAGRAMS: CCT+DALI (TCI DT6）




| Pout | SEC | 1 | 2 | 3 | 4 |
|---|---|---|---|---|---|
| 13W | 250mA | - | - | - | - |
| 19W | 350mA | - | - | - | ON |
| 20W | 400mA | - | - | ON | - |
| 20W | 450mA | - | ON | - | - |
| 20W | 500mA | - | - | ON | ON |
| 20W | 550mA | - | ON | - | ON |
| 20W | 600mA | - | ON | ON | - |
| 20W | 700mA | - | ON | ON | ON |
| 16W | 16mA | ON | ON | ON | ON |