









Circle

|              |  |
|--------------|--|
| Item code    | 86.A003.2401.01  |
| Product type | Indoor   |
| Category     | Architectural luminaires   |
| Family       | Circle   |
| Pictograms   |  220<br>240 V  CRI<br>80  SDCM<br>3  CE<br> Driver<br>INCL  IP<br>20 |

Scheme



|                           |                    |
|---------------------------|--------------------|
| Product                   |                    |
| Real power (W)            | 120W               |
| Real luminous flux (Lm)   | 10800              |
| Chip Brand                | Sanan              |
| Control gear              | ON-OFF             |
| Power Factor              | >0,95              |
| Average life time (h)     | L80 B20, 50,000hrs |
| Colour temperature (K)    | 4000K              |
| Colour consistency (SDCM) | SDCM3              |
| CRI                       | 80                 |