



Circle up&down

Lavov architectural lumnaire from the family Circle up&down with a power of Up 15W,Down 45W and a difuse lighting distribution. With a real lumen output of 1350/4050 lm. Made in Extruded aluminium and PC diffuser and finished in white color. Driver ON-OFF.

Item code	86.A001.1401.01		
Product type	Indoor Architectural luminaires		
Category			
Family	Circle up&down		
Pictograms	(±) 220 v CRI 80 SDCM 3 C€		
	Driver On IP INCL. Off 20		

Product	
Real power (W)	Up 15W,Down 45W
Real luminous flux (Lm)	1350/4050
Colour	white
Chip Brand	Sanan
Control gear included	yes
Control gear	ON-OFF
Power Factor	>0,95
Flicker Free	yes
Average life time (h)	L80 B20, 50,000hrs
Colour temperature (K)	4000K
Colour consistency (SDCM)	SDCM<3
CRI	80

Dimensions	
Product dimensions (mm)	60v80vdiam 1200

Scheme

