



Circle up&down

Lavov architectural lumnaire from the family Circle up&down with a power of Up 15W,Down 45W and a difuse lighting distribution. With a real lumen output of 1350/4052lm. Made in Extruded aluminium and PC diffuser and finished in silver color. Driver ON-OFF.

Item code	86.A001.1401.03 Indoor		
Product type			
Category	Architectural luminaires		
Family	Circle up&down		
Pictograms	220 v CRI SDCM 3		
	Driver On IP INCL. Off 20		

Product	
Real power (W)	Up 15W,Down 45W
Real luminous flux (Lm)	1350/4052
Colour	silver
Chip Brand	Sanan
Control gear included	yes
Control gear	ON-OFF
Power Factor	>0,95
Flicker Free	yes
Average life time (h)	L80 B20, 50,000hrs
Colour temperature (K)	4000K
Colour consistency (SDCM)	SDCM<3
CRI	80

Dimensions	
Product dimensions (mm)	60v80vdiam 1200

Scheme

