



Circle up&down

Lavov architectural lumnaire from the family Circle up&down with a power of Up 15W,Down 45W and a difuse lighting distribution. With a real lumen output of 1350/4050 lm. Made in Extruded aluminium and PC diffuser and finished in white color. Driver DALI.

Item code	86.A001.1403.01 Indoor Architectural luminaires Circle up&down	
Product type		
Category		
Family		
Pictograms	(cRI SDCM 3 C€	
	Driver INCL. IP 20	

Product	
Real power (W)	Up 15W,Down 45W
Real luminous flux (Lm)	1350/4050
Colour	white
Chip Brand	Sanan
Control gear included	yes
Control gear	DALI
Power Factor	>0,95
Flicker Free	yes
Average life time (h)	L80 B20, 50,000hrs
Colour temperature (K)	4000K
Colour consistency (SDCM)	SDCM<3
CRI	80

Dimensions	
Product dimensions (mm)	60x80xdiam 1200

Scheme

