










Scheme



Circle

Lavov architectural luminaire from the family Circle with a power of 150W and a diffuse lighting distribution. With a real lumen output of 13500lm. Made in Extruded aluminium and PC diffuser and finished in silver color. Driver DALI.

Item code	86.A003.3403.03
Product type	Indoor
Category	Architectural luminaires
Family	Circle
Pictograms	 220 240 V  CRI 80  SDCM 3  CE  Driver INCL  DALI  IP 20

Product	
Real power (W)	150W
Real luminous flux (Lm)	13500
Colour	silver
Chip Brand	Sanan
Control gear included	yes
Control gear	DALI
Power Factor	>0,95
Flicker Free	yes
Average life time (h)	L80 B20, 50,000hrs
Colour temperature (K)	4000K
Colour consistency (SDCM)	SDCM<3
CRI	80