



Trim cardan 2

Lavov downlight from the family Trim cardan 2 with a power of 2x17W and a beam angle of 20°. Finished in white colour. With a total lumen output of 2x1580lm and a luminous efficacy of 93lm/W. Made in die cast aluminium and PC lenses. Driver DALI dimmable . CCT 3000K.

Dimensions

Product dimensions (mm) L224*W112*H94mm

Scheme



Cut out : 102X212mm

| | |
|--------------|-----------------|
| Item code | 86.D091.1313.01 |
| Product type | Indoor |
| Category | Downlights |
| Family | Cardan |
| Subfamily | Trim cardan 2 |
| Pictograms | |

| | |
|----------------------------|-----------------|
| Product | |
| Real power (W) | 2x17 |
| Real luminous flux (Lm) | 2x1580 |
| Luminous efficiency (Lm/W) | 93 |
| Beam angle (º) | 20° |
| Life time (h) | 50000hrs L80B10 |
| IP | IP44 |
| Colour | white |
| Control gear included | yes |
| Control gear | DALI dimmable |
| Flicker Free | yes |
| Light source | led |
| Type of LED | COB |
| Colour temperature (K) | 3000 |
| Colour consistency (SDCM) | SDCM<3 |
| CRI | 90 |