


## Zoom Tube Smart

| | |
|---|---|
| **Item code** | **86.TST5.23Z9.01** |
| **Product type** | **Indoor** |
| **Category** | **Tracklights** |
| **Family** | **Tube & Zoom Tube** |
| **Subfamily** | **Zoom Tube Smart** |
| **Pictograms** |  |

## Scheme




| **Product** | |
|---|---|
| **Real power (W)** | **20** |
| **Real luminous flux (Lm)** | **1800** |
| **Luminous efficiency (Lm/W)** | **90** |
| **Beam angle (º)** | **20-50** |
| **Life time (h)** | **50000h L80B10** |
| **IP** | **20** |
| **Operating temperature** | **15** |
| **Chip Brand** | **Philip** |
| **Control gear** | **DALI Casamby ready** |
| **Colour temperature (K)** | **4000** |
| **Colour consistency (SDCM)** | **SDCM3** |
| **CRI** | **80** |