Item code 86.OU01.1331.07

- **Installation and wiring of luminaire must be in accordance with all applicabie local codes.**
- **Installation,inspection,and maintenance of luminaires should be performed by a qualified electrician.**
- **DO NOT make or alter any open holes in the luminaire Do not modify the luminaire.**
- **DO NOT install damaged product.**
- **Make sure electrical power is OFF before and during installation and maintenance.**
- **Make sure the equipment is properly grounded.**
- **Make sure the supply voltage is same as the rated fixture voltage.**

STEP 1



After placing the embedded bucket into the hole, keep it level with the ground at a 90 ° angle, and the power cord needs to pass through the embedded bucket
Attention: The height of the gravel should not be less than 25cm.

STEP 2



Connect one end of the power cord, wear into the embedded parts and keep them sufficient length of wire for easy to maintain.

STEP 3



Place the long power cord in the pre embedded bucket, then place the light fixture into the pre embedded bucket and tighten the screw.

STEP 4



Connect the IP67 waterproof connector The lighting fixtures should be kept at a depth of at least 1m.

CONNECTION DIAGRAM