




### PRO-DR Smart

Lavov downlight from the family PRO-DR Smart with a power of 12,2W and an optics 36 degrees . CCT 3000K. With a total lumen output of 787,5lm and a luminous efficiency of 64,56lm/W.DALI+wireless Casambi driver. Made in die cast aluminum and finished in grey color.

|                                    |  |
|------------------------------------|--|
| <b>Item code</b>                   | <b>86.DS25.1339.03</b>   |
| <b>Product type</b>                | <b>Indoor</b>  |
| <b>Category</b>                    | <b>Downlights</b>  |
| <b>Family</b>                      | <b>PRO-D</b>   |
| <b>Subfamily</b>                   | <b>PRO-DR Smart</b>  |
| <b>Pictograms</b>                  |  |
| <b>Product</b>                     |  |
| <b>Real power (W)</b>              | <b>12.2</b>  |
| <b>Real luminous flux (Lm)</b>     | <b>787.5</b>   |
| <b>Luminous efficiency (Lm/W)</b>  | <b>64.56</b>   |
| <b>Beam angle (°)</b>              | <b>36</b>  |
| <b>Life time (h)</b>               | <b>50000 h L80B10</b>  |
| <b>IP</b>                          | <b>20</b>  |
| <b>Electrical class insulation</b> | <b>Clas II</b>   |
| <b>Colour</b>                      | <b>grey</b>  |
| <b>Control gear included</b>       | <b>Yes</b>   |
| <b>Control gear</b>                | <b>DALI+wireless Casambi</b>   |
| <b>Flicker Free</b>                | <b>Yes</b>   |
| <b>Light source</b>                | <b>LED</b>   |
| <b>Type of LED</b>                 | <b>COB</b>   |
| <b>Colour temperature (K)</b>      | <b>3000</b>  |
| <b>Colour consistency (SDCM)</b>   | <b>SDCM3</b>   |
| <b>CRI</b>                         | <b>80</b>  |

### Scheme

