




### PRO-DS Smart

Lavov downlight from the family PRO-DS Smart with a power of 17,73W and an optics 12 degrees . CCT 3000K. With a total lumen output of 1556lm and a luminous efficiency of 87,76lm/W.DALI+ wireless Casambi driver. Made in die cast aluminum and finished in grey color.

|                     |   |
|---------------------|---|
| <b>Item code</b>    | <b>86.DS26.2319.03</b>  |
| <b>Product type</b> | <b>Indoor</b>   |
| <b>Category</b>     | <b>Downlights</b>   |
| <b>Family</b>       | <b>PRO-D</b>  |
| <b>Subfamily</b>    | <b>PRO-DS Smart</b>   |
| <b>Pictograms</b>   |  |

### Scheme



|                                    |                               |
|------------------------------------|-------------------------------|
| <b>Product</b>                     |                               |
| <b>Real power (W)</b>              | <b>17.73</b>                  |
| <b>Real luminous flux (Lm)</b>     | <b>1556</b>                   |
| <b>Luminous efficiency (Lm/W)</b>  | <b>87.76</b>                  |
| <b>Beam angle (°)</b>              | <b>12</b>                     |
| <b>Life time (h)</b>               | <b>50000 h L80B10</b>         |
| <b>IP</b>                          | <b>20</b>                     |
| <b>Electrical class insulation</b> | <b>Clas II</b>                |
| <b>Colour</b>                      | <b>grey</b>                   |
| <b>Control gear</b>                | <b>DALI+ wireless Casambi</b> |
| <b>Flicker Free</b>                | <b>Yes</b>                    |
| <b>Light source</b>                | <b>LED</b>                    |
| <b>Type of LED</b>                 | <b>COB</b>                    |
| <b>Colour temperature (K)</b>      | <b>3000</b>                   |
| <b>Colour consistency (SDCM)</b>   | <b>SDCM&lt;3</b>              |
| <b>CRI</b>                         | <b>80</b>                     |