



### Zoom Tube

Lavov Tracklight from the family Zoom Tube with a power of 30W and an optic of 20-50degrees with a total lumen output of 2250 lm and an efficiency of 75 lm/W. DALI driver.. CCT 4000 Kelvin. Made in Die cast aluminium and finished in Black colour. DALI driver.

<b>Item code</b>	<b>86.T005.34Z3.02</b>
------------------	------------------------

<b>Product type</b>	<b>Indoor</b>
---------------------	---------------

<b>Category</b>	<b>Tracklights</b>
-----------------	--------------------


<b>Family</b>	<b>Tube &amp; Zoom Tube</b>
---------------	-----------------------------

<b>Subfamily</b>	<b>Zoom Tube</b>
------------------	------------------

<b>Pictograms</b>	    
	    



### Scheme



### Product

<b>Real power (W)</b>	<b>30</b>
-----------------------	-----------

<b>Real luminous flux (Lm)</b>	<b>2250</b>
--------------------------------	-------------

<b>Luminous efficiency (Lm/W)</b>	<b>75</b>
-----------------------------------	-----------

<b>Beam angle (°)</b>	<b>20-50</b>
-----------------------	--------------

<b>Life time (h)</b>	<b>50000h L80B10</b>
----------------------	----------------------

<b>IP</b>	<b>20</b>
-----------	-----------

<b>Electrical class insulation</b>	<b>Class I</b>
------------------------------------	----------------

<b>Operating temperature</b>	<b>15</b>
------------------------------	-----------

<b>Colour</b>	<b>Black</b>
---------------	--------------

<b>Chip Brand</b>	<b>Philip</b>
-------------------	---------------

<b>Control gear included</b>	<b>YES</b>
------------------------------	------------

<b>Control gear</b>	<b>DALI</b>
---------------------	-------------

<b>Colour temperature (K)</b>	<b>4000</b>
-------------------------------	-------------

<b>Colour consistency (SDCM)</b>	<b>SDCM&lt;3</b>
----------------------------------	------------------

<b>CRI</b>	<b>80</b>
------------	-----------